

OptiPlex GX270

Marshall University Computing Services will not be held responsible for the use or misuse of this file. WARNING applying the incorrect BIOS to a computer system may cause damage.

The unpackaged file (GX270A03.EXE) can be used to flash the system BIOS from inside the Microsoft operating system. WARNING. Do not turn the system power off during the flash update. Note, Flashing the system from within the operating system is only supported in Microsoft Operating systems. Customers using Unix, Linux, Novell, or Solaris should create a DOS bootable diskette to copy this file to.

The file **GX270A03.EXE** is using the Hard Drive format and is designed to be directly executed from Windows environments.

Download

1. After reading the Export Compliance Disclaimer click **Download**

You will be asked to authenticate yourself by entering "**marshall\username**" and then your **password**.

2. Click the **Save** button.
The **Save As** window appears. |
3. Select **Desktop** using the drop-down menu to the right of **Save in**.
4. Click the **Save** button.
A progress meter moves as the download is completed.
5. If necessary, click **X** in the upper right-hand corner of the **Download Progress Window** to close it upon completion.

Install

1. Shut down all other applications prior to running the BIOS update utility. The update utility reboots your system in order to get the new BIOS loaded.
2. Double click the Icon on your desktop labeled GX270A03.EXE.
The **Dell Bios Flash** window appears
3. Click the **Continue** button.

The message **Pressing OK will close all applications, shut down Windows, Flash the BIOS, then reboot.** appears.
4. Click the **OK** button.
The system will restart and the Bios Flash will be completed.